

Cell2Jack Function Description

LED (small)

No light	: BT is not connected
Red	: BT is connected
Red Slow Flash	: BT is discoverable

LED (big)

Bright Blue	: Power ON and ON-HOOK
Dark Blue	: Power On and OFF-HOOK

Analog Phone DTMF Commands:

## or 0000	: Enter pairing mode
* or 1111	: Enable Siri / Google Talk (Rotary Feature)
2222XY	: Send XY commands

Option commands (Enter Keys from your home phone) (red is default)

89#	: Ring back testing	38#	: DTMF threshold Normal
2#	: Normal LED display	39#	: DTMF threshold High
3#	: Debugging LED display mode	41#	: No dialtone after call disconnect
10#	: General Dialing Plan with 10 sec timeout	42#	: Play dialtone after call disconnect
11#	: General Dialing Plan without timeout	43#	: Not reverse Tip/Ring after call disconnect
12#	: # only Dialing Plan	44#	: Reverse Tip/Ring after call disconnect
14#	: Enable Call Screening	50#	: Disable CID
15#	: Disable Call Screening	51#	: Enable CID
18#	: Enable Rotary Feature	60#	: Disable (Media Audio) A2DP streaming
19#	: Disable Rotary Feature	61#	: Enable (Media Audio) A2DP streaming
20#	: Regular Ringing strength	70# ~ 74#	: Off-Hook voltage: High, Medium, Low, Strong, Strongest
21#	: Strong Ringing strength	82#83#	: Clear Paired device and Reset parameters
24# ~ 28#	: Speaker volume level: 0, 1, 2 , 3, 4	80#	: Disable AEC
30# ~ 33#	: Hook detection 30, 50, 70, 100 ms	81#	: Enable AEC
35#	: Enable DTMF Tone Command	90# ~ 94#	: MIC volume level: 0, 1, 2 , 3, 4
36#	: Disable DTMF Tone Command	99#	: Reboot
37#	: DTMF threshold Low		

Option Features. (Setting with PC/MAC Application)

Echo Cancel Depth Control: Select Echo Depth.

Rotary Feature: 1111 Enable Siri or Google Voice. 5 seconds to dial independent of calling number length.

DTMF Input Scaling: Set DTMF detection input scaling value.

Dual Phone Connection:

1. Press '##' to pair first phone.
2. After connected, press '##' again to pair second phone.
(Note: Maximum pairing time is 300 seconds.)
3. After connected, both phones will be automatically re-connected once in range.
(Note: It will take up to 30 seconds to establish Bluetooth connection)

Hook Flash : Three way talk toggling, answer incoming call during Siri, Call waiting answering.
During streaming state, stop the streaming.

Dialing Plan: (Option to enable 5 seconds timeout or only use # to trigger dialing)

10 digits: first digit is not 0 nor 1.

11 digits: first digit is 1 and second digit is not 1.

3 digits : n11 (n = 2 ~ 9)

>10 digits: first digit is 0 end with # and length < 20

<10 digits: end with # and length >= 3

No digit for 10 seconds will trigger the dialing if stored digit number is > 5,

Rotary feature is 5 seconds.

*67 for no-CID outgoing call.

Call Waiting:

* key or hook flash to answer the new incoming call and hold current call.

* key or hook flash to switch back and forth between calls.

key to call conference both calls.